

# Signals and Spectra (1A)

---

Copyright (c) 2012 Young W. Lim.

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.2 or any later version published by the Free Software Foundation; with no Invariant Sections, no Front-Cover Texts, and no Back-Cover Texts. A copy of the license is included in the section entitled "GNU Free Documentation License".

Please send corrections (or suggestions) to [youngwlim@hotmail.com](mailto:youngwlim@hotmail.com).

This document was produced by using OpenOffice and Octave.

# Energy and Power

Instantaneous Power

$$p(t) = x^2(t) \quad \text{real signal}$$

Energy dissipated during  
(-T/2, +T/2)

$$E_x^T = \int_{-T/2}^{+T/2} x^2(t) dt$$

Affects the performance  
of a communication system

Average power dissipated during  
(-T/2, +T/2)

$$P_x^T = \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt$$

The rate at which energy is dissipated  
Determines the voltage

# Energy and Power Signals (1)

Energy dissipated during

$(-T/2, +T/2)$

$$E_x^T = \int_{-T/2}^{+T/2} x^2(t) dt$$

Average power dissipated during

$(-T/2, +T/2)$

$$P_x^T = \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt$$

## Energy Signal

Nonzero but finite energy

$0 < E_x < +\infty$  for all time

$$\begin{aligned} E_x &= \lim_{T \rightarrow +\infty} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \int_{-\infty}^{+\infty} x^2(t) dt < +\infty \end{aligned}$$

## Power Signal

Nonzero but finite power

$0 < P_x < +\infty$  for all time

$$\begin{aligned} P_x &= \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt \\ &< +\infty \end{aligned}$$

# Energy and Power Signals (2)

## Energy Signal

Nonzero but finite energy

$$0 < E_x < +\infty \text{ for all time}$$

$$\begin{aligned} E_x &= \lim_{T \rightarrow +\infty} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \int_{-\infty}^{+\infty} x^2(t) dt < +\infty \end{aligned}$$

## Power Signal

Nonzero but finite power

$$0 < P_x < +\infty \text{ for all time}$$

$$\begin{aligned} P_x &= \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt \\ &< +\infty \end{aligned}$$

$$\begin{aligned} P_x &= \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \lim_{T \rightarrow +\infty} \frac{B}{T} \rightarrow 0 \end{aligned}$$

$$\begin{aligned} E_x &= \lim_{T \rightarrow +\infty} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \lim_{T \rightarrow +\infty} B \cdot T \rightarrow +\infty \end{aligned}$$

Non-periodic signals  
Deterministic signals

Periodic signals  
Random signals

# Energy and Power Spectral Densities (1)

Total Energy, Non-periodic

$$E_x^T = \int_{-\infty}^{+\infty} x^2(t) dt$$

Average power, Periodic

$$P_x^T = \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt$$

Parseval's Theorem, Non-periodic

$$= \int_{-\infty}^{+\infty} |X(f)|^2 df$$

$$= \int_{-\infty}^{+\infty} \Psi(f) df$$

$$= 2 \int_0^{+\infty} \Psi(f) df$$

Parseval's Theorem, Periodic

$$= \sum_{n=-\infty}^{+\infty} |c_n|^2$$

$$= \int_{-\infty}^{+\infty} G_x(f) df$$

$$= 2 \int_0^{+\infty} G_x(f) df$$

Energy Spectral Density

$$\Psi(f) = |X(f)|^2$$

Power Spectral Density

$$G_x(f) = \sum_{n=-\infty}^{+\infty} |c_n|^2 \delta(f - n f_0)$$

# Energy and Power Spectral Densities (2)

## Energy Spectral Density

$$\Psi(f) = |X(f)|^2$$

Total Energy, Non-periodic

$$\begin{aligned} E_x^T &= \int_{-\infty}^{+\infty} x^2(t) dt \\ &= \int_{-\infty}^{+\infty} \Psi(f) df \end{aligned}$$

Parseval's Theorem, Non-periodic

## Power Spectral Density

$$G_x(f) = \sum_{n=-\infty}^{+\infty} |c_n|^2 \delta(f - n f_0)$$

Average power, Periodic

$$\begin{aligned} P_x^T &= \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \int_{-\infty}^{+\infty} G_x(f) df \end{aligned}$$

Parseval's Theorem, Periodic

Non-periodic power signal  
(having infinite energy) ?

# Energy and Power Spectral Densities (3)

## Power Spectral Density

$$G_x(f) = \lim_{T \rightarrow \infty} \frac{1}{T} |X_T(f)|^2$$

Non-periodic power signal  
(having infinite energy) ?

→ No Fourier Series

truncate

$$x(t) \rightarrow x_T(t) \quad \left(-\frac{T}{2} \leq t \leq +\frac{T}{2}\right)$$

→ Fourier Transform  $X_T(f)$

$$\begin{aligned} P_x^T &= \lim_{T \rightarrow \infty} \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \int_{-\infty}^{+\infty} \lim_{T \rightarrow \infty} \frac{|X(f)|^2}{T} df \end{aligned}$$

## Power Spectral Density

$$G_x(f) = \sum_{n=-\infty}^{+\infty} |c_n|^2 \delta(f - n f_0)$$

Average power, Periodic

$$\begin{aligned} P_x^T &= \frac{1}{T} \int_{-T/2}^{+T/2} x^2(t) dt \\ &= \int_{-\infty}^{+\infty} G_x(f) df \end{aligned}$$

Parseval's Theorem, Periodic



# Autocorrelation of Energy and Power Signals

## Autocorrelation of an Energy Signal

$$R_x(\tau) = \int_{-\infty}^{+\infty} x(t)x(t+\tau) dt$$

$(-\infty \leq \tau \leq +\infty)$

$$R_x(\tau) = R_x(-\tau)$$

$$R_x(\tau) \leq R_x(0)$$

$$R_x(\tau) \Leftrightarrow \Psi(f)$$

$$R_x(0) = \int_{-\infty}^{+\infty} x^2(t) dt$$

## Autocorrelation of a Power Signal

$$R_x(\tau) = \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} x(t)x(t+\tau) dt$$

$(-\infty \leq \tau \leq +\infty)$

## Autocorrelation of a Periodic Signal

$$R_x(\tau) = \frac{1}{T_0} \int_{-T_0/2}^{+T_0/2} x(t)x(t+\tau) dt$$

$(-\infty \leq \tau \leq +\infty)$

$$R_x(\tau) = R_x(-\tau)$$

$$R_x(\tau) \leq R_x(0)$$

$$R_x(\tau) \Leftrightarrow G_x(f)$$

$$R_x(0) = \frac{1}{T_0} \int_{-T_0/2}^{+T_0/2} x^2(t) dt$$

# Ensemble Average

## Random Variable

$$\begin{aligned} m_x &= \mathbf{E}\{X\} \\ &= \int_{-\infty}^{+\infty} \mathbf{x} p_X(\mathbf{x}) d\mathbf{x} \end{aligned}$$

$$\begin{aligned} \mathbf{E}\{X^2\} &= \sigma_x^2 + m_x^2 \\ &= \int_{-\infty}^{+\infty} \mathbf{x}^2 p_X(\mathbf{x}) d\mathbf{x} \end{aligned}$$

## Random Process

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} \\ &= \int_{-\infty}^{+\infty} \mathbf{x} p_{X_k}(\mathbf{x}) d\mathbf{x} \end{aligned}$$

for a given time  $t_k$

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} \\ &= \int_{-\infty}^{+\infty} \int_{-\infty}^{+\infty} \mathbf{x}_1 \mathbf{x}_2 p_{X_1, X_2}(\mathbf{x}_1, \mathbf{x}_2) d\mathbf{x}_1 d\mathbf{x}_2 \end{aligned}$$

# Ensemble Average

## Random Variable

$$\begin{aligned} m_x &= \mathbf{E}\{X\} \\ &= \int_{-\infty}^{+\infty} \mathbf{x} p_X(\mathbf{x}) d\mathbf{x} \end{aligned}$$

$$\begin{aligned} \mathbf{E}\{X^2\} &= \sigma_x^2 + m_x^2 \\ &= \int_{-\infty}^{+\infty} \mathbf{x}^2 p_X(\mathbf{x}) d\mathbf{x} \end{aligned}$$

## Random Process

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} \\ &= \int_{-\infty}^{+\infty} \mathbf{x} p_{X_k}(\mathbf{x}) d\mathbf{x} \end{aligned}$$

for a given time  $t_k$

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} \\ &= \int_{-\infty}^{+\infty} \int_{-\infty}^{+\infty} \mathbf{x}_1 \mathbf{x}_2 p_{X_1, X_2}(\mathbf{x}_1, \mathbf{x}_2) d\mathbf{x}_1 d\mathbf{x}_2 \end{aligned}$$

# WSS (Wide Sense Stationary)

## Random Process

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} \\ &= \int_{-\infty}^{+\infty} \mathbf{x} p_{X_k}(\mathbf{x}) d\mathbf{x} \end{aligned}$$

for a given time  $t_k$

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} \\ &= \int_{-\infty}^{+\infty} \int_{-\infty}^{+\infty} x_1 x_2 p_{X_1, X_2}(x_1, x_2) dx_1 dx_2 \end{aligned}$$



## WSS Process

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} \\ &= m_x \end{aligned}$$

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} \\ &= R_x(t_1 - t_2) \end{aligned}$$



# Autocorrelation of Random and Power Signals

## Autocorrelation of a Random Signal

$$R_x(\tau) = \mathbf{E}\{X(t)X(t + \tau)\}$$

$$R_x(\tau) = R_x(-\tau)$$

$$R_x(\tau) \leq R_x(0)$$

$$R_x(\tau) \Leftrightarrow G_x(f)$$

$$R_x(0) = \mathbf{E}\{X^2(t)\}$$

## Autocorrelation of a Power Signal

$$R_x(\tau) = \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} x(t)x(t + \tau) dt$$

$(-\infty \leq \tau \leq +\infty)$

## Autocorrelation of a Periodic Signal

$$R_x(\tau) = \frac{1}{T_0} \int_{-T_0/2}^{+T_0/2} x(t)x(t + \tau) dt$$

$(-\infty \leq \tau \leq +\infty)$

$$R_x(\tau) = R_x(-\tau)$$

$$R_x(\tau) \leq R_x(0)$$

$$R_x(\tau) \Leftrightarrow G_x(f)$$

$$R_x(0) = \frac{1}{T_0} \int_{-T_0/2}^{+T_0/2} x^2(t) dt$$

# Time Averaging and Ergodicity

## Random Process

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} \\ &= \int_{-\infty}^{+\infty} \mathbf{x} p_{X_k}(\mathbf{x}) d\mathbf{x} \end{aligned}$$

for a given time

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} \\ &= \int_{-\infty}^{+\infty} \int_{-\infty}^{+\infty} x_1 x_2 p_{X_1, X_2}(x_1, x_2) dx_1 dx_2 \end{aligned}$$

## WSS Process by ensemble average

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} \\ &= m_x \end{aligned}$$

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} \\ &= R_x(t_1 - t_2) \end{aligned}$$

## Ergodic Process by time average

$$\begin{aligned} m_x(t_k) &= \mathbf{E}\{X(t_k)\} = \\ m_x &= \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} X(t) dt \end{aligned}$$

$$\begin{aligned} R_x(t_1, t_2) &= \mathbf{E}\{X(t_1) X(t_2)\} = \\ R_x(t_1 - t_2) &= \lim_{T \rightarrow +\infty} \frac{1}{T} \int_{-T/2}^{+T/2} X(t) X(t+\tau) dt \end{aligned}$$

# Autocorrelation of Random and Power Signals

## Autocorrelation of a Random Signal

$$R_x(\tau) = \mathbf{E}\{X(t) X(t + \tau)\}$$

$$R_x(\tau) = R_x(-\tau)$$

$$R_x(\tau) \leq R_x(0)$$

$$R_x(\tau) \Leftrightarrow G_x(f)$$

$$R_x(0) = \mathbf{E}\{X^2(t)\}$$

## Power Spectral Density of a Random Signal

$$G_x(f) = \lim_{T \rightarrow +\infty} \frac{1}{T} |X_T(f)|^2$$

$$G_x(f) = G_x(-f)$$

$$G_x(f) \geq 0$$

$$G_x(f) \Leftrightarrow R_x(\tau)$$

$$P_x(0) = \int_{-\infty}^{+\infty} G_x(f) df$$

# Time Averaging and Ergodicity

---



## References

- [1] <http://en.wikipedia.org/>
- [2] <http://planetmath.org/>
- [3] B. Sklar, "Digital Communications: Fundamentals and Applications"