



in **STRIDE**

September 1982 • Vol. 1, Issue 1

CONTENTS:

g—System IV.21

LMI Forum

More RAM, New
Options & Prices

BIOS Changes

Disk Cache

Multiuser Installation

8-Track Tape Program

Square Root Program

People & Products

tech notes

New Tech Format For In Stride

by Valerie Joyce Bookman

Welcome to the In Stride Tech Notes! Stride has launched this new magazine, a daughter to its Stride[®], especially to support our users. It will concentrate on technical issues with the parent magazine. In Stride will address product and marketing concerns.

As a subscription, you get both magazines, so Stride will be published every third month (November is the next issue) while the Tech Notes will be published eight times a year, that is, every month that the parent isn't. This combo gives us a better way to publish actual programs, letters and files for user support (Yes! We have been listening) and still provide monthly product information.

Also, the six week preparation time for the strict color format meant real scheduling problems for a company that moves as fast as Stride. With our silly little laser printer, we ran both the Tech Notes through press in only about a week -- the information will be more timely and, hopefully, more accurate.

The new format is less costly to print, so the subscription price has been lowered accordingly. (See the back for pricing). Those of you who are owners and get it less probably don't care, but as we are getting more and more real user/developers this change allows us to offer the most information at a reasonable rate.

Despite the hassle from our third party software and hardware vendors, we've decided that the Tech Notes are not the place for ads. We'll still offer them in the In Stride. (February) November all space is full already and we're working on February). If you're a vendor and you want to buy a Stride ad, send us an article on some technical aspect of your system. It won't cost you anything either.

From the comments above, you can already tell that the Tech Notes are going to be have a much more "down home" style. Hopefully, the notes will cut through some of the marketing puff and prevail in our industry and get there to those that concern our users.

If talking about bugs and optimized code means you, there will still be plenty of reviews and how-to notes -- but skip over the other stuff.

If you don't like something speak up. We'd like to see more user letters, notes and tricky programming routines from you. It's best to send it in software Stride p-System, CP/MS-DOS or Unix style diskette format are best. That way, errors won't creep into the copy when someone types it.

The split in the new format should please those of you willing for more technical support and still let us direct our staff in fixing other more in a while.

In this attempt to add more "heat" to our publication, we can only quote the folks in the current Longtanger chain commercial:

"We're confident that this needs
with your approval..." ☐

Version IV.21 p-System Now Available

This issue denotes a lot of space to the details of the new IV.21 p-System release. That makes it only fair to tell you how to get it.

Historically, Stride offered versions IV.11A, IV.13 and IV.20 of the p-System operating system. Several important operational differences abound between IV.20 and IV.21. The IV.21 version has several new features and bug fixes, but code files are essentially compatible with IV.20.

In addition to the new p-System, Stride has updated the 486 Series BIOS and included several optimization features to speed up applications.

Stride continues to support our earlier computer line and a full release of IV.21 will be available for the Sage.

This new release will be shipped standard with every new machine starting October 15.

To upgrade to the p-System Pascal compiler, you have to provide proof of a prior purchase of the Program Development Kit. The PDK on your order is best.

Prices given are in US dollars, international folks must check with their dealers for pricing.

There are really three upgrade p-System IV.21 for the Stride 486 Series, p-System IV.21 for the Sage II and IV and the 486 Series BIOS upgrade.

It is a good idea to purchase the full

New Fast p-System Interpreter

Available in the new p-System IV.21 release (see below) is a new interpreter. The FASTINTERP file has optimized code for increased system speed, especially applications that do many string operations.

This is a special interpreter, not the standard TurboC release, and is contained only for Stride computers. It will not work on any version of the p-System prior to IV.21 so don't try to mix and match.

The new interpreter increases throughput from 10% to 50% depending on the application. ☐

p-System upgrade and not just the BIOS upgrade. The all-important IV.21 machine driver will be needed if you intend to order diagnostics and other support programs from Stride.

p-System IV.21 - 486 Series

Fast member SP100 is the run-time package which retails for \$60 and consists of the SYSTEM, UTILITY, and BIOS diskette.

SP100 includes the above plus the Pascal compiler and 16000 assembler on a fourth diskette called SDEV for \$100. (This requires prior purchase of the Program Development Kit).

p-System IV.21 - Sage II & IV

SP101 is the run-time package which retails for \$60 and consists of the SAGE, SDEV, and BIOS diskettes.

SP101 includes the above plus the Pascal compiler and 16000 assembler on a fourth diskette called SDEV for \$100. (This requires prior purchase of the Program Development Kit).

BIOS Update - 486 Series

DS100 contains a new 486 Series BIOS, MSUBIOS, UTILCODE and MSUTILCODE for \$25. ☐

Forth & CP/M-68K

by Ray Duncan

You have a program to develop. And a deadline to meet. You need a prototyping environment that makes your productivity soar. Do you turn to the Forth programming language?

Chances are that you don't — yet. Forth has long been recognized for its extremely efficient program development environment — a compiler/interpreter with an integral editor, assembler and other tools. But until recently, the Forth programmer had to give up all of his other development tools because Forth insisted on being an operating system in addition to a language.

Laboratory Microsystems has specialized in bringing Forth to operating systems that are industry-standard. We first brought a 2-80 Forth into the CP/M world. Then a 8088 Forth into the MS-DOS environment. Now, we have harnessed the power of 68000 Forth and put it within the CP/M operating system.

Exploiting CP/M-68K

How does Forth work with CP/M-68K? Simple. Forth appears as a CP/M "device" file, which is an executable code file to CP/M. When you invoke Forth (by typing its name), CP/M loads and runs the file, and you are in the Forth language environment.

Forth itself performs all I/O through CP/M-68K functions. For instance, console I/O is done through the BIOS (basic disk I/O, a part of CP/M) function that performs direct console character read and write.

Programs written in Forth are traditionally stored in Forth "objects." A screen in Forth is a text of source code that consists of 16 lines of 84 characters per line. LMI Forth stores screens like normal CP/M-68K files — they can be copied, deleted, etc., just as other CP/M-68K files. In the past, one reason for using Forth as an operating system was to gain a performance advantage over "general purpose" operating systems in reading and writing disk files. Stride has made this argument obsolete! Using a Sage II we recorded the amount of time needed

to load a file from a 40-track floppy disk and a RAM disk. The results are impressive — the RAM disk loads only 80% faster than the floppy disk!

Using the Power of Forth

LMI Forth is a highly optimized version of 80-standard Forth. The Forth Interest Group (FIG) publishes standards of interoperability for the Forth language. Their latest standard is Forth-80. LMI doesn't stop with the 80 Standard, though, but adds its own proprietary Forth features, assemblies, editors and CP/M-68K interfaces. Editing is done with a special Forth screen editor that responds to function(key) control codes. All of your favorite editing functions are there, in a "what you see is what you get" format.

One of Forth's unique features is the ease with which assembly language may be mixed with high-level code. In LMI Forth, a full Motorola 68000 assembler is on-line at all times.

To ease the transition into Forth, this assembler uses the Motorola mnemonics instead of a derived set.

Part of a Family

Forth users on the Stride are no longer so limited with LMI Forth. We make Forth-80 compilers for PC-104, MS-DOS, CP/M-68, CP/M-68, CP/M-68, CP/M-68, ProDOS and UNIX. And high-level Forth programs developed with one will run with all. Many computers run LMI Forth in bridge between home computers, PCs and superminis like the Stride.

For extremely large programs, LMI has developed a 31-bit version of Forth-80 that exploits the full addressing range of the 68000 processor. It allows you to write Forth programs up to the limit of your RAM space, yet it runs only 6-12% slower than the 16-bit version of LMI Forth.

Finally, for the most sophisticated users of Forth, there is the LMI Forth Meta Compiler. This program takes an

```
device: g8k
|
| | page = 68000 code base 68000 int 68000 00/0000 |
| |
| | 68000 68000-68000 68000 00/0000
| |
| | 68000 68000-68000 68000
| |
| |
| | 68000 68000 | 68000-68000 68000 --- 68000-68000 | |
| | 68000 68000 | | get function code from 680 |
| | 68000 68000 | | get parameter, name code |
| | 68000 68000 68000 | | convert to previous code |
| | 68000 68000 | | get page 68000 |
| | 68000 | | convert lower information |
| |
| |
| | 68000-68000 | get rid of assembler code |
| |
| |
```

```
device: g8k
|
| | get time from page 68000 00/0000 |
| |
| | 68000 68000 + 68000
| |
| |
| | 68000 | --- 68000-68000 | |
| | 68000 + | | get page no. code |
| | 68000 | | get page "next device" |
| | 68000 | | get time value in 68000 |
| |
| |
| |
| |
| |
| |
```

application developed in LAM Fortran and compiled in for a different processor. With it, you could use the Stride as a development system for IBM PC programs or for ROMed applications running on an 8031 microcomputer. Currently, the Stride Compiler can generate code for the 48600, 48800/90, 4890, E-80, 8051 and 8082 microprocessors and new processors are added each year.

A Fortran Example Using the Stride BIOS

Here's an example of how Fortran can be used with assembly language to extend and customize the language for the application at hand. Suppose you need to read the current time from the Stride clock under CP/M — trouble? CP/M-80C doesn't even know the clock exists, and has no way to access it in a portable fashion.

The builders of the Stride installed a very powerful BIOS (Basic I/O System) in the System ROM of the computer. To access it, you need to set the IO and AI registers of the 8080 and invoke TRAP 14. In screen 14, shown on the next page, the word BIOS takes the BIOS function number and the address of a buffer, performs the call and returns to high-level Fortran. As you can see, a "word" in Fortran is like a procedure or function in another language.

Using the new Fortran word is as simple as using any of the built-in words. In screen 14, the word BTIME (pronounced "bitz time") uses the Stride BIOS word to read the value of the system clock in bits of a second. Any other function of the Stride BIOS may be invoked simply by preparing a buffer of suitable length and using the BIOS word.

More Information

If you are interested in CP/M-80C, Fortran or have questions about it, feel free to call Laboratory Microsystems at (313) 388-1411. Our customer support bulletin board, at (313) 388-1310, carries news and information about LAM's latest products and includes a comprehensive database of both Fortran and non-Fortran public-domain programs. It is available between the hours of 9 p.m. and 5 a.m., Monday through Friday and all day Saturday and Sunday. ☐

Program Changes

Various small changes have been made in the following programs of the Stride p-System (V.2) release.

ALL MISCINFO file

If you have your own SYSTEMMISCINFO file, you will need to make the following changes before running on (V.2):

```
001 00000, 00017 000, 14 0000
002 000, 010 14 0000
003 *****
004 *****
005 *****
006 *****
007 000, 010 14 0000
008 000, 010 14 0000
```

TOPSYSI000E

A new file TOPSYSI2E replaces the old one. It has more features to allow file transfer on systems with only one floppy. (Our thanks to C. Emery of TEL Canada for the changes.)

TERMINALCODE

A new terminal selection is "STREET". It now accommodates new modem cards and patches SYSTEMMISCINFO for code post and market post options.

STRIDE.CODE & BALE.CODE

STRIDE.CODE is a new program for the 486 Series that figures out the memory size, disk size and BIOS version of the machine. It is set to display on boot.

BALE.CODE is the Page 2 and IV version of FUREL.CODE. ☐

My terminal's setup and the machine's serial port setup are different. How is worked. How come?

Settings such as 7 data bits with 1 stop bit will work on 2 data bits and 1 stop bit under most conditions — the number of total bits is equal. You must, however, make setups to always use correct operation. ☐

More Ram, New Options & Prices

Effective September 15, the standard minimum RAM for all Stride 486 Series systems is now 488K bytes. Previously the minimum was 588K bytes.

The new systems will feature 2MB, 4M, 6MB or 8M bytes of RAM in either 128K, 1M or 2M byte units.

Bigger Winchester

The Stride 486's now have an option for a 41M byte Winchester. The popular 10M was now replaced from the "cheap only" series announced this summer to this large storage configuration.

The 2800 byte hard drive option has been dropped from the 486 line. The smallest Winchester offered on the 486 is now 41M bytes.

Optional An Option

The Diamond Local Area Network is now an option in a chip set 14. All systems now connect to the network chips to make local installation easy. The new price for the LANA option is a very reasonable \$100 (total).

New Prices

Prices on the new systems with the Diamond chips, and with 121K bytes of RAM (888K bytes minus of RAM) will now be only \$84. This is a considerable savings when compared to the prior cost of a 486 system. ☐

Here are some useful tricks using the Stride (W)yes (W)ay-80 terminal:

If you need the terminal manually work and failed if you close it by typing the SETUP key (no shift) three times. This is also a fast way to avoid the function keys.

If you type ESC while in SETUP mode, all terminal parameters return to the Ripz factory default. ☐

Major Enhancements In The IV.21 p-System Release

The IV.21 version of the p-System has been released by World Wide for both 8086 and 8088 format machines. See the earlier article on earlier information.

In the discussion below, changes that occurred between versions IV.13 and version IV.21 are also so-remembered.

Applications that work under IV.08 need no changes to work under IV.21 unless you desire to take advantage of some of the new features.

External Code Pools

The IV.14 release (and IV.20) provides for management of multiple external code pools, based on the amount of available memory. Code space and data space are still restricted to 64K bytes. However, multiple code and data segments can now be resident in memory.

The operating system automatically adjusts this area for varying amounts of available memory provided the appropriate fields have been set in the SYSTEM.MEMINFO file in the machine's disc allowed. World distributed several different formatted versions of SYSTEM.MEMINFO in the subdirectory MEMC with the machine disc (RAMDISK type) set. Refer to the later article on Memory Management for details on how to define the value code and data pool sizes.

The routines in the new unit BETA.SHELL are needed to access the external pool areas.

Performance

The absolute time (time necessary to start program) for small memory machines (128K or less) is now much faster in IV.21. (Note: World does not officially support less than a 128K system, with typical memory needed per user being 150K.)

Changes have been made to provide a vastly improved boot time. Later world's IV.21 program innovation improvements and improvements to the PASC for the 80886 processors.

STARTUP Program

STARTUP is a new facility which allows you to run a set of commands at startup. The possibilities include most of the commands of the file and p-System command line. You can redefine the root volume (useful when loading a RAM disk) and also transfer the files over. Programs can be run one after another, subroutines invoked, etc.

This is a very useful facility for personalizing your own system's setup.

Hot Command

Hot is a new command in IV.20 releases. It is called from the main (command) p-System menu line. It allows you to set the following lines:

```
Hot
  Name
  Name is user
  Name's user is user
  Name's user
  Name's user
  Name's user
  Name's user
  Name's user
```

Note that you can still set the date and profile by using the file. The standard World DATE program is also available to set the clock.

The worldfile name is now designated using Hot. The file is no longer used for this purpose. Also, the SYSTEM.WRK form of the worldfile is no longer valid.

The Hot command displays information about the current configuration. This information includes what and whether package is installed, whether or not the print spooler is installed and the size of the code pool.

Editor

With version IV.14, the expense for updating a file was Qjot, Wjota, E, <C> and Ejectors. Then you could continue editing. With IV.14, this has been simplified. You can now save your file by typing W for Wjota. The file is saved under its original name. You do not know the file and your position in the file is kept.

With IV.14 when Qjot Update was used to edit the editor, the file "SYSTEM.WRK.TEST" was created. With IV.21, worldfile are treated differently. Qjot Update writes your file to disk with the same name that it had originally. See the comments on

the next page under Worldfile.

You can now use Qjot Write to write your test file to the PRINTER or any other serial volume.

Besides Tjot and Ljot, there are now two additional modes of searching in Fjot and Ejectors. They are Gtjot and Htjot. Gtjot enables the editor to search for a string but ignore whether the letters in that string are uppercase or lowercase. Htjot allows the editor to search for a string as it appears in the Pascal compiler; the case of the letters is ignored, underscores are ignored and only the first 4 characters are significant.

A new bar has been added to the Hot, Ejectors/Printer display. It indicates whether or not changes have been made since the file was last saved on disk.

A warning is given if you attempt to edit the editor without saving your changes.

File

The file no longer supports Qjot, Move, Write, or Now. These four commands were involved in manipulating the worldfile. The worldfile is now handled differently, see the paragraphs under Worldfile.

The Hot command now displays the file as a disk in two volumes instead of one.

The Updated hot command now displays the time that a file was last updated. This only happens, however, if the system time was set when the file was updated. The Hot command, the STARTUP program or the World DATE program may be used to set the system time.

Print Spooler

The print spooler now includes the ability to use wildcards in specifying the files to be printed and the ability to double special character handling when printing data files.

Version Identifier

When a p-System program starts to execute, the version number of that program is displayed in the following format:

[# # #]

In this format, the letters 'v', 'm' and 'r' denote versions, while the appropriate 'E' stands for "Edition" and is just used for expanding the letters 'v' and 'm'. The letter 'v' is the major release number, 'm' is the interim release

number and 'v' is the log file address number.

Compiler and Assemblers

For IV.16 releases, the compiler and assemblers create a code file with the same name as the text file when a simple <CR> is typed at the output file prompt. Previously, in version IV.14, the file SYSTEM.WRK.CODE was produced.

All compilers and assemblers now handle system errors in the same manner as the Pascal compiler. Each compiler or assembler has its own error file. In the case of the Pascal compiler, this is still SYSTEM.SYNTAX. When a system error is encountered, the compilation or assembly process. You are asked if you wish to continue or go to the editor. The editor automatically edits the file being processed even if it is an include file. If the source file is present, the error message is displayed on top of the screen. Otherwise, the error number is displayed.

The Pascal compiler has a new compiler option 'E'. When using the H- and M- keys to control a compiled listing, the 'E' command causes the listing to be exhibited in the state prior to the previous H- or M- command.

Debugger

Several new features have been added to the p-system debugger. (This is available on the program development disk.)

A command now displays the state of the stack.

Another command now allows you to look at disk memory so you could observe register state memory.

The environment list command has been improved.

Single stepping has been improved.

A command allows you to look at a code segment within the code pool.

Workfiles

Workfiles are handled differently from previous versions of the p-system. Now, the /SET command, not the /DIS, is used to designate the workfile. Also, SYSTEM.WRK.TEXT and SYSTEM.WRK.CODE workfiles do not exist in IV.16. The following summarizes how workfiles are now used.

Use the /SET command to designate a workfile name. First, the /TEXT and the /CODE file then begin with that

name are considered to be workfiles (if they exist).

Start the editor. The name of the workfile will be displayed. If you simply press <CR>, the workfile will be edited. However, you can backspace over the name and type in another name if you wish. (So you can add characters to the name displayed.)

Leave the editor by using /QUIT, /UPDATE. The output file has the same name as the original file had (SYSTEM.WRK.TEXT is not created.) If a code file with corresponding name exists on the same disk, that code file will be removed. Note that simply using /QUIT /UPDATE does not mean that the output file is the workfile; the first command must be used to define the workfile.

Start a compiler or assembler by pressing C or A. The name of the workfile is displayed on the file to be compiler or assembled. In with the editor, if you simply press <CR>, that file is processed. However, you can clear the name displayed and the new name will be the file compiled. The prompt for the code file is then displayed. If you simply type <CR>, the output code file is given the name that corresponds to the text file. You can enter a different code file name if you wish.

If you start the compiler by typing H for HINT, instead of C for COMP, the workfile is always compiled and the output code file is always given the name that corresponds to the input text file. (The prompts for the file to be compiled and the output code file are not displayed.)

Pascal Language Enhancements

The USER Pascal Manual describes the Pascal language under the p-system. There are some enhancements to the language which were made after the last publication of the book. Refer to the Program Development Reference Manual for details on Pascal enhancements.

Version IV.14 contains these new enhancements:

- statement arrays
- variable enhancement arrays
- function and procedure parameters
- FOR next value enhancement
- exit code
- improved label on case
- improved label structure

A Constant Array is a Pascal type which allows you to pass different sized

arrays as the same parameter to a routine (after separate calls to that routine). An Interface Constant Array is a similar type which allows you to pass variables of different types as well as data in the same parameter to a routine (after separate calls to that routine). Features were found with the implementation of Constant arrays under IV.16, which have been fixed in the new IV.16 release.

The Function and Procedure Parameters enhancement allows you to pass functions and procedures as parameters to routines. For example, you can pass one procedure as a parameter to another procedure.

The HIDEF include allows you to determine the size of any variable or Pascal type. This feature can now return the size of a structure in units other than bytes. It also can return the size of a particular field within a record.

Each code map is specified for each procedure in the same manner that initialization code is specified for UNITS. This feature is very useful for user maintainable code.

The 'Intrinsic map' feature is now much easier to use. You need only to specify the identifiers that you explicitly use. In IV.14 you had to specify not only the identifiers that you explicitly used but also the names of sub-structures that you used.

The code generated by the Pascal compiler is slightly better than that generated by previous versions of the compiler. If you compare an old program the new code file is usually smaller than the old code file.

Processes

Concurrent processes in Pascal are necessary on the /loop for their own sake. Three individual stacks are used by processes in the same way that the main p-system stack is used by non-concurrent code. (For example, variables are stacked there.) With IV.16 this /loop queue is released when a process terminates. This was not the case with IV.14. In addition, processes can be terminated by other processes (see the Error Handling /sub) and are automatically terminated by an EXIT/PROXIMAL statement.

Closing Files

Editing is desirable to open an existing file (using HSET) and also create a new file (using HWRITE)

(Continued)

bank of which have the same name. During the time both files are open, the old file is a "premanent file" and the new file is a "temporary" file.

Previously, the order in which the two files were closed did not matter. The CLOSE (C) with a LOCK or a CHANGE on the new temporary file would change its status to a closed premanent file. At the same time, the old file would be removed.

With V.11, you must first CLOSE the old file before closing the new file. This order is now important since the old file is "locked" during the time it is open and therefore cannot be removed by other operating system commands.

The difference between version V.10 and V.11 does require your application to be changed and recompiled.

Real Time CLOCKUNIT

A new unit called CLOCKUNIT supports setting and reading a real-time clock. The original STRIKE time and date unit, TIME UNIT is the TOPOLINKS library has not been changed. New programs written with capability to read real-time clock machines should use the CLOCKUNIT routine.

A new program called SETCLOCK was obtained by NetTech, but it is not distributed by Strite. The DATE program is still the user program for setting the system time and date.

System Units

Changes have been made to the literature versions of the following units. The changes are fully described in the Program Development Reference Manual.

```
*****
*****
*****
*****
*****
*****
*****
*****
```

Any V.10 programs using NERNEI should be recompiled.

Two new routines are included in SCREENOPS to handle reading long strings. This does not affect any programs which currently use SCREENOPS.

ERRORHANDLER has many new features. It now allows you to handle execution errors, cancel processes, and

translate I/O and execution error numbers into English text. These additions should not affect any programs which currently use ERRORHANDLER.

The file management units, WILD, BRANFS, STRNFS, and FILENFS, contain additional routines. The WILD unit will also allow your program to set two new "wildcard" (?) and (!). These additions should not affect any programs which currently use these units.

TRANSFER is a new unit which allows your program to move files in the same way that the file's Transfer command does.

ATTRIBUTES is a new unit to retrieve the various attributes of a file such as type, date etc.

DATETIME allows a program to manage a date area (the extra CODE and DATE post) outside of the stack/heap area. In addition, data can be passed between programs using this mechanism. □

Reading Foreign UNIX Floppies

It is sometimes necessary to read foreign floppies under UNIX systems. Some foreign UNIX systems that writing tape information on the second track. The Strite tape program expects data to start on the first track.

You can use the dd program to take care of differences such as this. For example:

```
cc (cc)cc/cddr ccdd (cc)cc -f(cc)cc
```

This will read a foreign tape formatted diskette which was written with bit byte sectors starting at the second track. □

UNIX office Station

The office program which generates C programs, has problems is currently incompatible with the configuration of the C compiler and lsm. The conflict has been worked for the next UNIX release.

400 Series BIOS Changes

A new BIOS, MESSAGE, UTE_CODE and MUTIL_CODE are available in the October release, either combined with the V.11 release or separately, with the BIOS update disk.

.....

None of these changes require any recompilation of your programs.

.....

Modifications to support new versions of tape drives were made to the QCODE unit.

Various serial channel driver changes were made, mostly to provide better compatibility between 400 Series and Ray communications routines.

The Winchester drives and buffer handling were modified for better Linkon network operation and the Disk Cache feature.

An minor change was made to the Clock Circuit driver to deal with a critical problem which only occurred when writing the date on the last day of March, May, July, October or December.

An on-line configuration change to the attach numbers now works correctly. □

Manual Types

Appendix A on pages 488 and 489 of the Golden Operating System manual, lists the Distribution Drive numbers incorrectly. Each drive number is one too large.

On page 488-489 of Volume 2 of the Strite Owner's manual, the effects numbering for the serial channel data format is incorrect. Each effect group shows one byte. The sequence for the groups should be 0-8.

9-Track Tapes A "FIT" For Sirdle

By Judy Olson and Mark Bergerson

Virtually all mainframes and minis can read and dump data and text files on reel-to-reel, 9-track end-to-end tapes. The Sirdle microcomputer now has that capability with a software and hardware package developed by a group in Corvallis, Oregon. The Sirdle FITS (Half-Inch Tape Subsystem) provides an easy means for transferring mainframe volumes of data between the Sirdle and any mainframe or minicomputer, as well as means to keep volumes of data privately stored on magnetic tape.

The FIT Team

Jackie Gordon of ViaAbility, Corvallis, Oregon, is a researcher in atmospheric optics. For her contract with the Army Research Office she needed a tape drive to access a large volume of data that only existed on half-inch, end-to-end magnetic tape. ViaAbility already owned a Sirdle II and had bought a Sirdle 400 for its large Winchester disk and because the VMEbus allowed the addition of proprietary sub-systems. Jackie planned on using her Sirdle 400 to process her data, but first needed a means of transferring it from the archive tapes onto the Winchester disk.

Jim Gordon (another partner of ViaAbility and associate professor at Oregon State University) attempted to locate a tape subsystem for the Sirdle. After a number of phone calls and attending the Sirdle Expo in February, 1983, he was able to locate a number of people who were also interested in a tape drive system, but no one who could provide it.

Jim then talked to Mark Bergerson (of R-100 Systems, Corvallis, Oregon), a friend and hardware/software consultant. Mark had built his first computer in MIT and has written 30000 assembly language programs for a number of computer systems. He felt he could handle any of the problems involved with developing a tape drive system (with the cost, however, could not be justified for a single person working on a single project). But if a package were

put together for resale . . .

With the addition of another friend, Sirdle dealer JET Number 101 Maritime Information, Ltd., the Sirdle FITS team was formed. Development work would be done under ViaAbility with Mark handling the hardware interface and programming. Marketing, distribution and support would be through Maritime Information, Ltd.

The FITS Product

The Sirdle FITS hardware consists of a Sirdle 400 or 408 (this system is not recommended for the 408), a Kennedy tape drive, model 8000 or 9000, and the FITS kit (Silver Materials board, two of which are connected as a single pluggable module, and three connecting cables). Four compatible drives can be daisy-chained in the system.

The software consists of three main components, a control unit, a utility program and a hard disk backup program. They presently run only in the p-System environment.

The **Tape Control Unit** is a package of Assembly routines which interface the tape drive. It can be linked with Pascal or FORTRAN code under the p-System. Source code for the Tape Utility Program will be included as an example program using the Tape Control Unit.

The **Tape Utility Program** is used to drive a file-to-tape and tape-to-file capability for transferring tape files to hard disk. It also can be used to investigate a tape of unknown format by printing the data on the screen in either ASCII or HEX. It has block-by-block and file-by-file spooling capabilities, forward and backward.

The **Tape Backup Program** (to be menu driven) allows the user to read and write in a tape-to-disk or disk-to-tape manner. Whereas the Tape Utility Program copies single files, the Tape Backup Program copies whole volumes. It also has the reading ability necessary for archiving purposes. Of the three software pieces, the Tape Backup Program has the most built in sub-routines.

Besides the Materials board and cables, Tape Control Unit, Tape Backup program, Tape Utility program and source code, a Sirdle FITS buyer will also receive a manual and automatic notification of updates. For the first year after purchase, a buyer will receive free any software updates applying to the purchaser's original operating system, upon request. After

the first year there will be an item-by-item charge. Additional FITS system programming is available by special arrangement with the FITS Group.

Further plans include integrating the Sirdle FITS into the single user RISC to allow access to the tape drive as a Sirdle drive. The current FITS version runs only under the p-System operating system whereas the RISC is common to all operating systems. Adaptations to additional multi-operating systems are also anticipated.

TECHNICALITIES

The just-released Kennedy 8000 tape drive is a perfect match for the Sirdle. It is compact and robust, with both crossover and step/scan modes at 300 and at 175 respectively. It can use either 8000 or 800 FIT tapes and has full diagnostic features. Its front load feature handles all reel sizes up to 1/2" and it is reasonably priced. Three or four 8000s can be installed in the vertical space occupied by an older volume control drive. The Kennedy model 9000 provides a low expense and slower option, at 1000 FIT only.

The tape controller hardware consists of two sub-systems, the VMEbus I/O adapter and the FIT (Signal/Tape) adapter. The I/O adapter plugs into the VMEbus on the Sirdle and decodes the VMEbus short address mode signals. It also handles the requirement of various leverages for the processor. The I/O adapter decodes a segment of the VMEbus short address space. It then passes it to the FIT adapter address bits, data bits and timing signals. These signals are exchanged over a ribbon cable which plugs into a connector on each unit. The FIT adapter also receives its +5V power from the I/O adapter via this cable. There is a manufacturer's warranty on both boards.

The FIT adapter (two 1/2" VME slots, pluggable card) further decodes the address space selected by the I/O adapter to enable the selection of a block of contiguous registers or consecutive odd addresses. These registers are used to control operation of the tape deck and also to read data and status from the tape deck. Control, status and data signals are exchanged between the FIT adapter and the tape deck over two ribbon cables.

Mark Bergerson encountered some problems in integrating the magnetic tape system into the Sirdle 400

microcomputers. These required some hardware modifications of the I/O adapter to interface it with the Stride. Much of the development effort was spent in solving problems involving floating address bits and VME timing sequences.

After these problems were solved, Mark wrote assembly-language procedures to communicate with the tape deck. These are linkable with p-System Pascal or FORTRAN programs and can be used to read and write data on 1/2-inch magnetic tapes in a number of different formats. The proper decoding of the blocks read from the tapes is a function of the host Pascal or FORTRAN p-System program. The prototype assembly language procedures did not modify the language structure of the Stride BIOS and used only polled I/O to communicate with the tape deck. Even with these constraints, data could be written to tape at more than 150 kbps per minute using the Kennedy model 1600 tape deck running in start-stop mode at 45 inches per second. With further optimization of the tape read and write routines, data transfer rates can be doubled or tripled for disk backup purposes, particularly with faster operating systems.

Software Operation

Tape Utility Program (TUP)

From a menu one of the following:

1. Read a tape.
2. Write to tape.
3. Append (Pascal/Strided or FORTRAN only).
4. Repartition (Strided tapes).
5. Read a block from the tape.
6. ASCII display of tape data.
7. Miscellaneous status of tape deck.
8. EXIT to a menu.

See below for:

The Tape Utility program allows the user to determine the characteristics of newly-arrived tapes, display the data on the tape in either hexadecimal byte or ASCII character format and to move single disk files to and from the tape.

This last capability has been of particular value to VLSI, which uses tapes of atmospheric data with files more than 750 bytes long.



The model 1600 Kennedy tape drive used with the TUP program offers 1/2 IPI start/stop and 300 IPI streaming performance along with automatic tape loading.

A tape file is read into a disk file in a large partition of the hard disk on the Stride OS. Pascal programs can then access the data using standard data file manipulation techniques.

The Tape Utility is a menu-driven program which allows the user to use the RTT system with only a few keystrokes at the terminal. The menu for the preliminary version of the program is shown to the left. This menu is subject to change as the program is updated.

The **Tape to File** menu selection prompts the user for the name of the disk file in which the tape should be written. If a file by that name already exists, the user is asked if the file should be overwritten. The user is also asked if the tape file has a descriptive header block. If the response is positive, this block will be read and displayed on the screen, but not written to the disk file.

File to Tape transfers a disk file selected by the user to the magnetic tape. The file is written at the End of Data (EOD) position on the tape. The EOD position consists of two consecutive End of File (EOF) blocks. The EOF mark is then written after the new file. The data from the disk file is preceded by a short header block which names the disk file and specifies

the date and date of the transfer to tape. This is the block that is normally ignored when the file is transferred back to disk. There must be a Write Flag in place on the tape or the program will notify you that the tape is write-protected.

The **File to Tape** and **Tape to File** commands are instructed to allow the user to manipulate files which are too large to be conveniently stored on floppy disk. The requirement that new files be appended to the disk already on the tape makes these commands only marginally useful for clean data and program files.

The **Append** command actually requires the user to enter two more characters before the tape deck is activated. The second character (P or N) specifies the direction to move the tape. The third character (F or B) specifies whether the tape should move to an EOF mark or just over a single tape block. For example, the characters BFF would cause the tape to move forward to the next file mark.

The **Readback** command is the computer controlled equivalent of the rewind button. The tape deck remains in the Run and ready to read the first block on the tape.

The **Read** command reads the next block on the tape into an internal buffer.

(Continued)

The **ASCII display** command displays the data in the tape buffer in ASCII character format. The data is displayed 20 lines at a time. A line is defined as either 80 consecutive characters or a series of characters followed by a Carriage Return character. After 20 lines are displayed, the user can either hit the Escape key to return to the main menu, or any other key to display the next 20 lines. Control characters are not displayed.

The **Hexadecimal display** command displays the data in the tape buffer as a 4 byte hexadecimal address followed by 16 bytes in hexadecimal format, then 16 ASCII characters (quoted characters are replaced by periods).

Initializing a tape simply means writing two consecutive DDP marks at the beginning of the tape. Then, any Future File to Tape commands will start writing at the beginning of the tape, overwriting any previous data on the tape. Since this command can potentially destroy data on the tape, the user must verify the command to initialize the tape. A Write Flag must also be in place on the tape.

Features Options

The following product information shows the options available on the RTN package.

All options include the following software: Tape Control Disk, Tape Utility Program and Tape Storing Program.

Order #21

\$4,995 120 cassette tapes
Support to Tape Archive System
All necessary cables

\$1,695 5000 RTN 20 unit
500 RTN 20 unit
500 RTN 20 unit
500 RTN 20 unit

\$1,995/ \$2,995 5000 RTN 20 unit
500 RTN 20 unit
500 RTN 20 unit
500 RTN 20 unit

The package with the Kennedy model 9800 is available at the introductory price of only \$1899 until December 31, 1991.

RTN is distributed by Marketing Information, Ltd., 8888 Riverchase Road, Covellville, OR. Contact J. Swisher (402) 728-2242 ☐

400 Series DISK CACHE Improves Winchester Hard Disk Throughput

The Disk Cache is a new feature of the Model 400 Series BIOS and MULTIBIOS available with the p-System IV. It replaces the BIOS update disk.

The Disk Cache is an area of memory (usually 112K or more) set aside by the user for use by the hard disk drives. Information is read from the disk is "cached" in this memory area. Obviously, the cache cannot hold the entire contents of the disk. Tracks are stored as they are read and written with the "next nearby user" tracks being replaced by the new tracks.

READ Operation

When a track is read from the disk, it is also copied. If the track requested is already in the cache, it is read from the cache, not from the disk.

Therefore, the first read to a track is at regular disk speed. However, the second read of that same track will take place at memory access speed, not the slower hard-disk access speed.

Applications which frequently access the same information will find that the Disk Cache will significantly improve throughput as it is much faster to read memory than disk.

WRITE Operation

When a track is written to the disk, it is also written to the cache. As cache memory can be lost due to a power failure, machine reset, etc., a write operation is always done to the disk, ensuring the integrity of the files. This means that a write operation is actually a **WRITE SLOWER** than non-cache operation because the extra step of writing the cache takes a little more time.

RAM DISK = DISK CACHE

Disk Cache is very similar in operation to RAM disk. In fact, you install it in almost exactly the same way. However, it provides several important advantages over RAM disk.

It is safe. Disk Cache operation ensures that data is saved on the hard disk. RAM disk data will vanish if power is lost or the system is reloaded.

Fast data is faster. Files and data do not have to be loaded to the RAM disk. This eliminates loading in place which files to get into RAM disk.

More data can be accessed. RAM disk only works for the files and data stored on it. Disk Cache works for all data on all the hard disks.

Disk Cache Installation

The Disk Cache is installed using a new command in UTIL.UTILCODEM and MULTIBIOS under the RAM disk option. Utility recommendations that you back up your old system files before installing any of the new files on your system.

The new version of the multibios installation program MULTIBIOS will automatically assign new buffers necessary to the Disk Cache if the amount leftover is greater than or equal to 112K bytes.

The same Disk Cache will handle multiple drives and all partitions that are made accessible to the operating system by the SYSTEMBIOS or MULTIBIOS configuration. ☐

What is <RTN> ?

<RTN> is a key command used in "Value" an operation in the p-System, usually in the Editor. On the 200 Series and the 400, (which use a CTRL/C) push the Ctrl key down while typing "C").

To register the <RTN> command in the SYSTEMARCHINFO.MB, use the SETUP.COM program.

Square Root Speed

by G. A. Gallop

For a number of years my students and I have been developing and running a package of computer programs for performing molecular electronic structure calculations. We have tested and run them on a number of different computer systems. Through these comparisons, we discovered that the running time of one particular program in our set, varied considerably more from machine to machine than the basic machine speeds would warrant. Further investigation showed that a computer in which the square root function was implemented in hardware gave the fastest time for our program.

This particular program segment must calculate the distance between pairs of several thousand points in three dimensional space. This requires the three dimensional Pythagorean theorem and all three square roots — in double precision, too.

I have now converted these programs to a Fortran 4th. Previous experience led me to examine how rapidly square roots were handled in the program where this is crucial. Timing tests showed that the IBM FORTRAN library routine for DSQRRT takes, on the average, 1.8 microseconds to execute.

I felt this was rather sluggish and thought that it might be possible to get more speed with a different type of function substitution. While examining the possibilities, I recalled the old-fashioned "long division" method for calculating square roots that we were all taught in grade school and considered that an assembly routine using binary arithmetic could implement this method entirely within the registers of the 80000.

The eight long word data registers available on the 80000 are indeed sufficient for the task. The assembly language shows single and double precision square root routines that in the worst case take only 40% of the time of the FORTRAN routine. The single precision version is normally faster than that.

(Continued)

- Listing 1. Subroutine for square roots by the long division method in the registers of the 80000.
-

program	FORTRAN	IBM360 computer time for FORTRAN compiler
• FORTRAN usage: program SQUARE square root of REAL number A		
•		
=====		
FORTRAN: device 1	0000.00	1 instance of program
device 2	1000.000	1 instance of 1000
device 3	00-00-0000	1 case 00-00-0000
device 4	1000.00	1 set program, 1 set for data
time	00000	1 set program, 1 set for data
job	00	1 test for job 00, 00, 00
device 5	00.00	
job	000.00	• load error message
time	00	
device 6	00.00	
time	00000	
device 7	00.00	
device 8	00.00	
device 9	00.00	
job 10	00.00	• load error message
time	00.00	
device 11	0000.00	
device 12	00000000.00	
device 13	00000000.00	
device 14	00.00	
device 15	00000000.00	
device 16	0000.00	
job 17	00.00	
time	000	
device 18	00.00	
job 19	00.00	
device 20	00.00	
time	000	
device 21	00.00	
device 22	00.00	
device 23	00.00	
device 24	00.00	
device 25	00.00	
device 26	00.00	
device 27	00.00	
device 28	00.00	
device 29	00.00	
device 30	00.00	
device 31	00.00	
device 32	00.00	
device 33	00.00	
device 34	00.00	
device 35	00.00	
device 36	00.00	
device 37	00.00	
device 38	00.00	
device 39	00.00	
device 40	00.00	
device 41	00.00	
device 42	00.00	
device 43	00.00	
device 44	00.00	
device 45	00.00	
device 46	00.00	
device 47	00.00	
device 48	00.00	
device 49	00.00	
device 50	00.00	
device 51	00.00	
device 52	00.00	
device 53	00.00	
device 54	00.00	
device 55	00.00	
device 56	00.00	
device 57	00.00	
device 58	00.00	
device 59	00.00	
device 60	00.00	
device 61	00.00	
device 62	00.00	
device 63	00.00	
device 64	00.00	
device 65	00.00	
device 66	00.00	
device 67	00.00	
device 68	00.00	
device 69	00.00	
device 70	00.00	
device 71	00.00	
device 72	00.00	
device 73	00.00	
device 74	00.00	
device 75	00.00	
device 76	00.00	
device 77	00.00	
device 78	00.00	
device 79	00.00	
device 80	00.00	
device 81	00.00	
device 82	00.00	
device 83	00.00	
device 84	00.00	
device 85	00.00	
device 86	00.00	
device 87	00.00	
device 88	00.00	
device 89	00.00	
device 90	00.00	
device 91	00.00	
device 92	00.00	
device 93	00.00	
device 94	00.00	
device 95	00.00	
device 96	00.00	
device 97	00.00	
device 98	00.00	
device 99	00.00	
device 100	00.00	

MAIL RATE
U.S. POSTAGE
P & D
PERMIT #102
BIRMINGHAM, ALABAMA

Editors: Verlene Ayers Beaman

In Stride Test Notes is a publication of Stride Motors, issued eight times yearly. Subscriptions are \$11 for one year and include the *In Stride* parent magazine which is published quarterly, for a total of 11 issues per year.

Test Notes back issues are also available for \$1.00 and *In Stride* back issues for \$1.00 an supply lasts.

Purchase of a Stride computer includes a one-year subscription upon receipt by Stride Motors, Essex, of a fully completed owner's registration card.

Requests for subscriptions, reprint permission, ad rates, bulk orders or submission of prospective articles should be sent to the *In Stride* Editor at Stride Motors's Essex address.

Postmaster: Change of address notices should be sent to:

In Stride Editor
Stride Motors
P.O. Box 20018
Essex, NY 13020-0018
(518) 837-6555 (8 a.m. - 4 p.m. EST)
TWX 410-365-0873

Stride Motors Eastern Division
112-118 Washington Street
Methuen, MA 01844
(617) 838-0700

Stride Motors Southern Division
12740 Reed Road
Dallas, TX 75240
(214) 361-7600

Stride™, Performance By Design™ and RCR™ are trademarks of Stride Motors.

©Copyright 1993-1994 Stride Motors
All Rights Reserved Worldwide

STRIDE
Performance By Design